

FACTORY RESET TO DEFAULT VALUES FOR 740 LOGIX FILTER CONTROL

- 1) TO RESET CONTROL PRESS AND HOLD DOWN ARROW AND SET BUTTON FOR '5" SECONDS
- 2) PRESS AND HOLD SET BUTTON FOR AN ADDITIONAL "5" SECONDS
- 3) DISPLAY WILL SHOW THREE DASHES AND A DECIMAL POINT
- 4) DISPLAY WILL BE FLASHING, CONTROL IS RESET

INITIAL SETUP PROGRAMMING 740 LOGIX FILTER CONTROL

SET FUNCTION TYPE

- 1) PRESS UP/DOWN ARROWS TO SCROLL THRU VALVE TYPES
- 2) SELECT "F"
- 3) PRESS "SET" TO ACCEPT

SET TIME OF DAY

- 1) PRESS "SET" TO CHANGE VALUE
- 2) PRESS UP/DOWN ARROWS TO SCROLL TO CORRECT TIME
- 3) PRESS "SET" TO ACCEPT

SET DAY OF WEEK

- 1) PRESS "SET" TO CHANGE VALUE
- 2) PRESS UP/DOWN ARROWS TO SCROLL TO CORRECT DAY
- 3) PRESS "SET" TO ACCEPT

SET REGENERATION TIME

- 1) PRESS "SET" TO CHANGE VALUE
- 2) PRESS UP/DOWN ARROWS TO SCROLL TO DESIRED REGEN TIME (2:00 AM IS DEFAULT)
- 3) PRESS "SET" TO ACCEPT

SET DAY OVERRIDE

- 1) PRESS "SET" TO CHANGE VALUE
- 2) PRESS UP/DOWN ARROWS TO SCROLL TO DESIRED DAYS BETWEEN REGEN
- 3) SELECT 3 (DEFAULT = 3)
- 4) PRESS "SET" TO ACCEPT

SET BACKWASH LENGTH

- 1) PRESS "SET" TO CHANGE VALUE
- 2) PRESS UP/DOWN ARROWS TO SCROLL TO DESIRED DAYS BETWEEN REGENERATION
- 3) SELECT 10 (DEFAULT = 14)
- 4) PRESS "SET" TO ACCEPT

INITIAL PROGRAMMING IS COMPLETE AND YOU WILL NOW RETURN TO NORMAL OPERATING MODE